

**Блоки Питания ЭЛТИС**

БП	Клеммы	Питание основных блоков	Питание э/м замка	Питание видео	Вход упр-ния	ПРИМ
<b>PS2-C2</b>	Y1	~15V ( $\pm 10\%$ ) $I_H = 0,3A$				
	Y2					
PS2-C1	+U		+12V ( $\pm 10\%$ ) $I_H = 0,6A$			
PS3-C1	-U					
<b>PS2-CS2</b>	Y1	~15V ( $\pm 10\%$ ) $I_H = 0,3A$				
	Y2					
PS2-CS1	ZNC		+12V ( $\pm 10\%$ ) $I_H \leq 0,6A$			0V по OUT
PS3-CS1	ZC (-)					
PS3-CS2	ZNO		revers			+12V по OUT
	OUT				+	
<b>PS2-CE2</b>	Y1	~15V ( $\pm 10\%$ ) $I_H = 0,3A$				
	Y2					
PS3-CE1	LE-		+12V ( $\pm 10\%$ ) $I_H \leq 0,6A$			0V по OUT
PS3-CE2	LE+					
	OUT				+	
<b>PS2-CSD2</b>	+U	+17V ( $\pm 10\%$ ) $I_H = 0,8A$				
для DP201	GND					
	ZNC		+12V ( $\pm 10\%$ ) $I_H \leq 0,6A$			0V по OUT
	ZC (-)					
	ZNO		revers			+12V по OUT
	OUT				+	
<b>PS2-CS2D</b>	+U	+17V ( $\pm 10\%$ ) $I_H = 0,3A$				
для DP1	GND					
	ZNC		+12V ( $\pm 10\%$ ) $I_H \leq 0,6A$			0V по OUT
	ZC (-)					
	ZNO		revers			+12V по OUT
	OUT				+	
<b>PS2-DKV3</b>	+18	+18V ( $\pm 5\%$ ) $I_H \leq 0,5A$				
	-18					
	+13		+13V ( $\pm 5\%$ ) $I_H \leq 0,6A$			
	-13					
	-12			+12V ( $\pm 5\%$ ) $I_H \leq 0,6A$		
	-12					
	13S		+13V ( $\pm 5\%$ )			0V по OUT
	OUT				+	